

SPOT 575 XT- DMX PROTOCOL

[illegible]

[illegible]

Mode 1 channel	Mode 2 channel	8 bit channel	Value	Function	Type of control
12	12	10	0-127 128-190 191-192 193-255	Rotating gobo index, rotating gobo rotation Gobo indexing Forwards gobo rotation from fast to slow No rotation Backwards gobo rotation from slow to fast	proportional proportional step proportional
13	13	11	0 1-179 180-191 192-223 224-255	Iris Open Max.diameter to min.diameter Closed Pulse closing from slow to fast Pulse opening from fast to slow	step proportional step proportional proportional
14	14	12	0-85 86-170 171-225	Focus, multistep zoom Zoom 15°-Continuous adjustment from far to near Zoom 18°-Continuous adjustment from far to near Zoom 22°-Continuous adjustment from far to near	proportional proportional proportional
15	15	13	0-31 32-63 64-95 96-127 128-159 160-191 192-223 224-255	Shutter, strobe Shutter closed No function (Shutter open) Strobe-effect from slow to fast (max.10 flashes/s) No function (Shutter open) Pulse-effect in sequences from slow to fast No function (Shutter open) Random strobe-effect from slow to fast No function (Shutter open)	step step proportional step proportional step proportional step
16	16	14	0-255	Dimmer intensity Gradual adjustment of the dimmer intensity from 0 to 100%	proportional